Forming machines

PHOTO



2000 S basic version

2000S is a pneumatic machine for the forming and cutting of untaped electronic component terminals.

Thanks to the interchangeability of the forming blades and the distance pieces, this machine copes with the most demanding needs


2000 S is supplied with its cutting mask. Several forming masks are available on request (see next paragraph)

Basic version.

	weight kg	cutting capacity comp/h
170x90x80	4	1000-1500

TECHNICAL SPECIFICATIONS







2000 S 1000 holes version

2000S is a pneumatic machine for the forming and cutting of untaped electronic component terminals.


Thanks to the interchangeability of the forming blades and the distance pieces, this machine copes with the most demanding needs

2000 S is supplied with its cutting mask. Several forming masks are available on request (see next paragraph)

1000 holes version

	weight kg	cutting capacity comp/h
170x90x80	4	1000-1500








2000 SE basic version
2000S is an electric machine for the forming and cutting of untaped electronic component terminals.


Thanks to the interchangeability of the forming blades and the distance pieces, this machine copes with the most demanding needs

2000 SE is supplied with its cutting mask. Several forming masks are available on request (see next paragraph)

Basic version.

	weight kg	cutting capacity comp/s
200x280x95	10	1300-1800







2000 SE 1000 holes version


2000S is an electric machine for the forming and cutting of untaped electronic component terminals.

Thanks to the interchangeability of the forming blades and the distance pieces, this machine copes with the most demanding needs

2000 SE is supplied with its cutting mask. Several forming masks are available on request (see next paragraph)

1000 holes version

	weight kg	cutting capacity comp/h
200x280x95	10	1300-1800





Forming masks cod. MTA The "c" value TO 18 PREF A - TO 18 2.54 1.27 Forms and cuts 2.54 pitch transistors. Possibility to increase the D measure by spacing the MTA mask 1.40 4.00 cod. CTA rred to cod. MTA 5 boards of TO 5 **PREF A5 - TO 5** 5.08 Forms and cuts 5.08 pitch transistors. 2.54 Possibility to increase the D measure 1.40 by spacing the MTA5 mask 4.00 thic cod. CTA 5 cod. MLD LED PREF B - LED 2.54-5.08 Forms and cuts 2.54 pitch led with the MLD mask, or 5.08 pitch led with the MCC mask. Possibility to increase 1.40 (short 3.50 the D measure by spacing the MLD or MCC masks 0.60 cod. CLD CAPACITOR **PREF C - CAPACITOR** 5.08 Forms and cuts the leds of 5.08 pitch 2.00 capacitors. Possibility to increase the D measure by spacing the MCC mask 3.50 cod, CCC cod. MTC LED - CAPACITOR PREF D - LED / CAPACITOR 2.54 For cutting leds and capacitors when 1.50-4.50 short side polarity needs to distinguished. Possibility to increase the C measure by spacing the MTC mask 0.60 cod. CTC cod, MTA5 TO220 **PREF E - TO220** 1.50 Forms and cuts the leds of TO 220 4.00 components. Possibility to increase the D and the G measures by spacing 2.54 the MTA5 mask cod. CTM cod. MTA5 PREF F - TO220 TO 220 1.50 Forms at 90° angle and cuts the leds of TO 220 components, leds and 2.50 capacitors. Possibility to increase the I measure by spacing the MTA5 mask 2.54 cod. C90 cod. MTA4 OSCIL PREF G - OSCILLATOR 7.62 Forms and cuts oscillators. Possibility 1.50 to increase the D measure by spacing the MTA4 mask 4.00 cod. CT4 cod. MCC TO220 TO 220 CAPACITOR/ LED TO 220 Forms and cuts TO220 components conden/led and capacitors. Possibility to increase the D measure by spacing the MTA5 mask (for TO220), the MCC mask (for capacitors), the MLD mask (for leds). 1.40 4.00

cod. CCH

